

30 AMP

Features


POWERS HARD-WIRED CIRCUITS
no need for extension cords

Pre-wired for **QUICK AND EASY INSTALLATION**

PUSH-BUTTON change between utility and generator power

POWER SOURCE INDICATING LIGHTS
utility and generator

Accessories



25 FT. POWER CORD



POWER INLET BOX



30 AMP

L14-30P



L14-30R



Specifications

AMPERAGE (A)	30
VOLTAGE (V)	240
ENCLOSURE RATING	NEMA 1 (Indoor)
CIRCUITS	8
BREAKERS INCLUDED	1-30A 2-pole 1-20A 1-pole 5-15A 1-pole
WHIP LENGTH	59 in. (12 in. flexible conduit)
COMPLIANCE	UL 1008 / CSA C22.2 No. 178.1
CORD RECEPTACLES	L14-30P, L14-30R
INLET BOX RECEPTACLE	L14-30P

Champion's 30-Amp manual transfer switch is prewired and has 8 circuits, so you no longer need extension cords to get power from your generator into your home. The switch allows you to easily change between utility and generator power, while the LED lights indicate active power sources: utility, generator, or both.

Inside the box

INSTALLATION MANUAL
PRE-WIRED MANUAL TRANSFER SWITCH

25 FT. (7.6 M) POWER CORD
POWER INLET BOX

What You Need

50A 2-POLE CIRCUIT BREAKER
NM-B ELECTRICAL WIRE
ELECTRICAL CONDUIT

CONDUIT FITTINGS
WIRE CONNECTIONS

*Specifications, descriptions and illustrations are subject to change without notice.

PACKAGE (gross)
Weight: 43.2 lb.
Size: 20.3 x 19.5 x 12 in.

PRODUCT (net)
Weight: 33.1 lb.
Size: 17.6 x 15.3 x 4.4 in.