

# 50 AMP

## Features

**POWERS HARD-WIRED CIRCUITS**  
no need for extension cords

Pre-wired for **QUICK AND EASY INSTALLATION**

**PUSH-BUTTON** change between utility and generator power

**POWER SOURCE INDICATING LIGHTS**  
utility and generator

## Accessories



30 FT. POWER CORD



POWER INLET BOX



## Specifications

AMPERAGE (A)	50
VOLTAGE (V)	240
ENCLOSURE RATING	NEMA 1 (Indoor)
CIRCUITS	10
BREAKERS INCLUDED	2-30A 2-pole 2-20A 1-pole 2-20A 1-pole tandem
WHIP LENGTH	59 in. (12 in. flexible conduit)
COMPLIANCE	UL 1008 / CSA C22.2 No. 178.1
CORD RECEPTACLES	14-50P, SS2-50R
INLET BOX RECEPTACLE	SS2-50P

Champion's 50-Amp manual transfer switch is prewired and has 10 circuits, so you no longer need extension cords to get power from your generator into your home. The switch allows you to easily change between utility and generator power, while the LED lights indicate active power sources: utility, generator, or both.

### Inside the box

**INSTALLATION MANUAL**  
**PRE-WIRED MANUAL TRANSFER SWITCH**

**30 FT. (9.1 M) POWER CORD**  
**POWER INLET BOX**

### What You Need

**50A 2-POLE CIRCUIT BREAKER**  
**NM-B ELECTRICAL WIRE**  
**ELECTRICAL CONDUIT**

**CONDUIT FITTINGS**  
**WIRE CONNECTIONS**

\*Specifications, descriptions and illustrations are subject to change without notice.

**PACKAGE (gross)**  
Weight: 55.1 lb.  
Size: 20.3 x 19.5 x 12 in.

**PRODUCT (net)**  
Weight: 48.1 lb.  
Size: 17.6 x 15.3 x 4.4 in.