



POWERING YOUR *life.*

Model 201407

UPC 817198027807

Warranty 3 Years

11000
STARTING WATTS

9000
RUNNING WATTS

RUN TIME 15 hrs. NOISE LEVEL 64 dBA

ELECTRIC START
Push-button start includes **BATTERY**

INTELLI GAUGE
5-MODE display

ULTRA QUIET
LOW NOISE - high performance

COVERED OUTLETS
PROTECT outlets from the elements

Receptacles

12V DC Regulated Automotive

20 AMP GFCI 120V, 5-20R

20 AMP GFCI 120V, 5-20R

37.5 AMP 120/240V, L14-30R

30 AMP 120/240V, L14-30R

Specifications

START TYPE	Wireless, Electric, Recoil
VOLTAGE (V) AC [DC]	120/240 [12]
VOLTMETER	Intelligauge w/ Power Meter
ENGINE SIZE (cc)	459
FUEL TYPE	Gasoline
GASOLINE CAPACITY (gal.)	6.08
OIL TYPE	10W-30
OIL CAPACITY (fl. oz./mL)	37.2/1100
LOW OIL SHUT-OFF	Yes
EMISSIONS	EPA III

*Specifications, descriptions and illustrations are subject to change without notice.



CARBON MONOXIDE AUTO-SHUTOFF



Champion's 9200-watt natural gas ready generator features CO Shield® carbon monoxide auto shutoff system. Also operating on Tri-Fuel technology, allowing it to run on natural gas, gasoline, or propane. This unit meets ANSI/PGMA G300-2023 requirements and includes a 25-foot natural gas hose kit.

Inside the box

GENERATOR	REMOTE KEY FOB	OPERATOR'S MANUAL
WHEEL KIT	SPARK PLUG SOCKET	OIL FUNNEL
BATTERY	ALLEN WRENCH	ENGINE OIL

What You Need

GASOLINE
WRENCH/SOCKET SET

PACKAGE (gross)
Weight: 227.1 lb.
Size: 29.5 x 25.6 x 29.9 in.

PRODUCT (net)
Weight: 200 lb.
Size: 28.3 x 28.8 x 27.5 in.