



POWERING YOUR *life.*

Model 201506

UPC 817198028552

Warranty 3 Years

10000 STARTING WATTS **8000** RUNNING WATTS

RUN TIME 10 hrs. NOISE LEVEL 74 dBA



ELECTRIC START
Push-button start includes **BATTERY**



INTELLI GAUGE
4-MODE digital meter



COVERED OUTLETS
PROTECT outlets from the elements



VOLT GUARD
Protects against **POWER SURGES**



COLD START
Easy starts in **COLD WEATHER**

Receptacles



30 AMP
120/240V, L14-30R



33.3 AMP
120/240V, 14-50R



20 AMP GFCI
120V, 5-20R



20 AMP GFCI
120V, 5-20R

Specifications

START TYPE	Wireless, Electric, Recoil
VOLTAGE (V) AC	120/240
VOLTMETER	Intelligauge
ENGINE SIZE (cc)	458
FUEL TYPE	Gasoline
GASOLINE CAPACITY (gal.)	7.7
OIL TYPE	10W-30
OIL CAPACITY (fl. oz./mL)	40.6/1200
LOW OIL SHUT-OFF	Yes
EMISSIONS	EPA III



CARBON MONOXIDE AUTO-SHUTOFF SYSTEM



Our 8000-watt generator with remote key fob allows you to wirelessly start and stop your generator from up to 80 feet away and features CO Shield® carbon monoxide auto shutoff system. The 458cc Champion engine with electric start and included battery has all the power you need for home backup during an outage or your next project.

Inside the box

GENERATOR	OPERATOR'S MANUAL
WHEEL KIT	OIL FUNNEL
REMOTE KEY FOB	ENGINE OIL
BATTERY	

What You Need

GASOLINE
WRENCH/SOCKET SET
PLIERS

*Specifications, descriptions and illustrations are subject to change without notice.

PACKAGE (gross)
Weight: 211.6 lb.
Size: 31.1 x 22.8 x 24.1 in.

PRODUCT (net)
Weight: 198.4 lb.
Size: 28.8 x 27.4 x 25.8 in.